

GEE 4 16KHz Call metering (for TLA)	S30817-H951-M313	x	x	-	-	x	x	x	x	x	x	x	x
UAM Announcement before Answering	(Ländervarianten) country variants	x	x	-	-	x	x	x	x	x	x	x	x
OPAL Options Adapter Long	C39195-A7001-B130	x	x	-	-	x	x	x	x	x	x	x	x
STBG4 (For France only)	S30817-Q934-A	x	x	-	-	x	x	x	x	x	x	x	x
STRB Actors/Sensors	S30817-Q932-A	x	x	-	-	x	x	x	x	x	x	x	x
V24/1 V24/1 interface (not for CBCC -A401)	S30807-Q6916-X100	x	x	-	-	x	x	x	x	x	x	x	x
IVMS8 8 ports Integrated voice mail for 3550	S30122-Q7379-X	-	x	-	-	x	x	x	x	x	x	x	x
IVMS8N (8 Port) new Integrated voice mail for 3350/3550 (with hard disc)	S30122-K7379-X200	x	x	-	-	no	no	no	no	x	x	x	x
IVMP8 Integrated voice mail for 3350	S30122-Q7379-X100	x	-	-	-	x	x	x	x	x	x	x	x
IVMP4 (4 Port) Integrated voice mail for 3350/3550 (without hard disc)	S30122-Q7721-X	x	x	-	-	no	no	no	no	x	x	x	x
EVM, Entry Voice Mail for CBCC S30810-K2935-A301/ A401 CBRC S30810-K2935-Z301/ Z401	S30807-Q6945-X	x	x	x	x	no	no	no	x	x	x	x	x
SLU8 Digitale Subscriber Line (U _{rx})	S30817-Q922-A301	x	x	-	-	x	x	x	x	x	x	x	x
4SLA Subscriber Line Analog Ringing voltage (a/b) 75 V	S30810-H2923-X200	x	x	-	-	x	x	x	x	x	x	x	x
SLAD4 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF-	S30810-H2956-X100	x	x	-	-	no	no	no	no	V6.0R11.1.0 bind831	V7R4.3.0, bind 42	x	x
8SLA Subscriber Line Analog Ringing voltage (a/b) 75 V	S30810-H2923-X100	x	x	-	-	x	x	x	x	x	x	x	x
SLAD8 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver	S30810-H2956-X200	x	x	-	-	no	no	no	no	V6.0R11.1.0, bind 831	V7R4.3.0, bind 42	x	x
16SLA Subscriber Line Analog Ringing voltage (a/b) 75 V	S30810-H2923-X	x	x	-	-	x	x	x	x	x	x	x	x
SLAD16 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver, planned in Sept. 09	S30810-H2957-X	x	x	-	-	no	no	no	no	open	x	x	x
HXGS LAN-Board	S30810-Q2931-X	x	x	-	-	x	x	x	no	no	no	no	no
HXGS2 LAN-Board HG1500 V2	S30810-Q2939-X	x	x	-	-	x	x	x	no	no	no	no	no
HXGS3 LAN-Board HG1500 V3	S30810-Q2943-X	x	x	-	-	no	V3.0	V3.0	V5.0	V6.0	V7.0	V8	x
HXGS3 (new as of V8) LAN-Board HG1500 V3	S30810-Q2943-X1	x	x	-	-	no	no	no	V8	V8	V8	V8	x
PDM1 extension module for HXGS3/HXGR3	S30807-Q5692-X100	x	x	x	x	no	x	x	x	x	x	x	x
STLS2 S0-Trunk- / Subscriber Line	S30817-Q924-B313	x	x	-	-	x	x	x	x	x	x	x	x
STLSX2 new S0-Trunk- / Subscriber Line	S30810-H2944-X100	x	x	-	-	no	no	no	x	x	x	x	x
STLS4 S0-Trunk- / Subscriber Line	S30817-Q924-A313	x	x	-	-	x	x	x	x	x	x	x	x
STLSX4 new S0-Trunk- / Subscriber Line	S30810-H2944-X	x	x	-	-	no	no	no	x	x	x	x	x

TLA2 Analog Trunk Line	S30817-H923-B313 = Germany S30817-H923-Bxx = Country var.	x	x	-	-	x	x	x	x	x	x	x	x
TLANI2 new Analog Trunk with CLIP	S30810-Q2953-X100 = Germany S30810-Q2953-X1xx = Country	x	x	-	-	no	no	no	no	R10.0.0	x	x	x
TLA4 Analog Trunk Line	S30817-H923-A313 = Germany S30817-H923-Axx = Country var.	x	x	-	-	x	x	x	x	x	x	x	x
TLANI4 new Analog Trunk with CLIP	S30810-Q2953-X = Germany S30810-Q2953-Xxx = Country var.	x	x	-	-	no	no	no	no	R10.0.0	x	x	x
TLA8 Analog Trunk Line	S30817-H926-Axx = Country var.	x	x	-	-	x	x	x	x	x	x	no	no
TS2 (Trunk Module S2M)	S30817-H2913-X100	-	x	-	-	x	x	x	x	x	x	x	x
TS2 (Trunk Module S2M) new	S30810-H2913-X300	-	x	-	-	no	no	no	x	x	x	x	x
SLC16 (old) Cordless	S30810-Q2922-X	-	x	-	-	x	x	x	x	no	no	no	no
SLC16N Cordless	S30810-Q2193-X100	-	x	-	-	x	x	x	x	x	x	x	x
CBRC, Motherboard (as of issue E2 for 64MB MMC)	S30810-K2935-Z	-	-	x	x	no	no	x	no	no	no	no	no
CBRC incl. EVM, Motherboard Ringing voltage (a/b) 35 V (as of issue C1 for 64MB MMC)	S30810-K2935-Z301	-	-	x	x	no	no	no	x	x	x	x	x
CBRC neu Integrated LIM and EVM, 1 x V24 Ringing voltage (a/b) 65 V	S30810-K2935-Z401	-	-	x	x	no	no	no	x	x	x	x	x
HXGSR2 LAN-Board HG1500 V2	S30810-K2939-Z100	-	-	x	x	no	no	no	no	no	no	no	no
HXGSR3 LAN-Board HG1500 V3	S30810-K2943-Z	-	-	x	x	no	no	V3.0	V5.0	V6.0	V7.0	V8	V8
HXGSR3 (new as of V8) LAN-Board HG1500 V3	S30810-K2943-Z1	-	-	x	x	no	no	no	x	x	x	V8	V8
IMODC analog mode up to 14,4 kbit/s	S30807-Q6932-X	x	x	x	x	x	x	x	x	x	x	x	V8
IMODC analog mode up to 33,6 kbit/s	S30807-Q6932-X100	x	x	x	x	x	x	x	x	x	x	x	V8
IVMS8R HiPath Xpressions Compact V2.0	S30122-K7379-Z	-	-	-	x	x	x	x	x	x	x	x	x
IVMP8R HiPath Xpressions Compact V2.0	S30122-K7379-Z100	-	-	x	-	no	no	x	x	x	x	x	x
IVMP4R (4 Port) HiPath Xpressions Compact V2.5 (without hard disc)	S30122-K7721-X	-	-	x	x	no	no	no	no	SMR8	x	x	x
IVMS8NR (8 Port) HiPath Xpressions Compact V2.5 (with hard disc)	S30122-K7379-Z200	-	-	x	x	no	no	no	no	SMR8	x	x	x
EVM, Entry Voice Mail	S30807-Q6945-X	x	x	x	x	no	no	no	x	x	x	x	x
UAM Announcement before Answering	S30122-X7217-X country variants	x	x	-	-	no	no	x	x	x	x	x	x
OPALR Options Adapter Cable Long Rack)	C39195-A7001-B142	-	-	x	x	no	no	x	x	x	x	x	x
SLU8R Digitale Subscriber Line (U _{rx})	(S30817-K922-Z301	-	-	x	x	no	no	x	x	x	x	x	x
STLS4R S0-Trunk- / Subscriber Line	S30817-K924-Z313	-	-	x	x	no	no	no	x	x	x	x	x
STLSX4R new S0-Trunk- / Subscriber Line	S30810-H2944-Z	-	-	x	x	no	no	no	x	x	x	x	x
STRBR Control Relay Board Rack	S30817-H932-Z	-	-	x	x	no	no	x	x	x	x	x	x

TLA4R Analog Trunk Line	S30817-Q923-Zxxx country variants	-	-	x	x	no	no	x	x	x	x	x	x
TLAN4R new Analog Trunk Line	S30810-Q2953-X2xx (X200 = GER)	-	-	x	x	no	no	no	no	R10.0.0	x	x	x
UAMR Announcement before Answering	S30122-X7402-Z	-	-	x	x	no	no	x	x	x	x	x	x
8SLAR Subscriber Line Analog Ringing voltage (a/b) 75 V	S30810-K2925-Z	-	-	x	x	no	no	x	x	x	x	x	x
SLADR8 new with CLIP Subscriber Line Analog Ringing voltage (a/b) 75 V, DTMF- receiver	S30810-K2956-X300	-	-	x	x	no	no	no	no	ab V6.0R11.1.0, bind 831	ab V7R4.3.0, bind 42	x	x
EBR Extension-Box-Rack	S30777-U711-E901	-	-	x	x	no	no	x	x	x	x	x	x
EPSU2 external power supply unit	S30122-K7221-X2	x	x	-	-	no	no	no	x	x	x	x	x
EPSU2-R external power supply unit		-	-	x	x	no	no	no	x	x	x	x	x