

## In Idle State

Function	DISA phone number + DTMF code	Explanation
Dial a number	[Call no.]	Dial the DISA phone number and enter the destination number as a DTMF code.
Program or Delete call forwarding	* 1 1 + [call no.] or # 1	Dial the DISA phone number, enter the DTMF code and (when programming) the call number of the forwarding destination.
Activate or Deactivate Do Not Disturb	* <sup>EXT 9</sup> <sup>EXT 7</sup> or # <sup>EXT 9</sup> <sup>EXT 7</sup>	Dial the DISA call no. and enter the DTMF code. This enables or disables the DND feature (e.g., after business hours, during vacations, at home).
Send message	* <sup>EXT 6</sup> <sup>EXT 8</sup> + [Call No. Int. Stn.] + [Digits 1 ... 9]	Dial the DISA call no. and enter the DTMF code. Enter the call number of the internal station and dial a digit for the message. The message is sent to the internal station.
Reset all services	# 0	Dial the DISA call no. and enter the DTMF code. The following services are reset: deleting call forwarding and active callback requests, deactivating the Do-Not-Disturb and station number suppression (CLIR) features.
Calling Line Identification Restriction (CLIR) On/Off	* <sup>EXT 8</sup> <sup>EXT 6</sup> or # <sup>EXT 8</sup> <sup>EXT 6</sup>	Dial the DISA call no. and enter the DTMF code. This suppresses or presents the call number for subsequent calls.

Always include the CO access code (trunk code) when dialing an external destination call number.

## In Talk State

Function	DTMF code	Explanation
Consultation	[Call No. of 2nd. Stn.]	Dial the call number of the second party. This initiates a consultation hold and places the first party on hold.
Toggle/Connect (Prerequisite: a call is on consultation hold)	* <sup>EXT 2</sup>	Enter the DTMF code to switch to the next waiting party.
Conferencing (Prerequisite: a call is on consultation hold)	* <sup>EXT 3</sup>	Enter the DTMF code to connect multiple parties to a call.
Disconnect and return to held call (Prerequisite: a call is on consultation hold)	* 0	Enter the DTMF code to end the consultation call. You are reconnected to the waiting party.
Activate callback (delete in idle state using # 0)	* <sup>EXT 5</sup> <sup>EXT 8</sup>	Enter the DTMF code to activate a callback ("Callback on busy" or "Callback on No Answer). The callback is requested after the ringback or busy tone is played. Acknowledgement is provided by a positive or negative confirmation tone (no display).
Enable DTMF suffix dialing	* <sup>EXT 5</sup> <sup>EXT 3</sup>	Enter the DTMF code. This forwards the next DTMF code "transparently", e.g., to control a voicemail system.

### ATTENTION!

Please note that you cannot make any emergency calls via Mobility Entry, since so no local mapping to the mobile phone is possible for such calls.

# Mobility Entry

## Quick Reference Guide

Mobility Entry enables you to use the features of your communication system from your mobile phone or your mobile home office.

With Mobility Entry, you can use the features your communication system without additional hardware and software requirements just as you are accustomed to as an internal subscriber by simply dialing your DISA phone number.